MANUFACTURER DOCUMENT PACKAGE

Manufacturer's Manual

Reference package for procurement and maintenance review

HONEYWELL

CC-TDIL51 51307083-175

DIGITAL INPUT TERMINATION ASSEMBLY

Used with the applicable Experion Series C configuration.

REFERENCE PACKAGE

OFFICIAL DOCUMENT

Selected official manufacturer pages follow this cover.

Source: Honeywell CC-TDIL51

Honeywell

Technical Information

Experion Series-C I/O Specification



EP03-490-520

Release 520

Dec 2021, Version 1.5

Table of Contents

1. Product Introduction Summary 4
1.1. Overview 4
1.2. Scope 4
1.3. Definitions 4
2. Features 4
3. Series C I/O Sizing 5
3.1. I/O Module Functions 5
4. I/O Module Sizes 6
5. Specifications 8
5.1. Analog Input with HART – CC-PAIH01 / 02 8
5.2. Analog Input with HART – CC-PAIH51 10
5.3. Analog Input – CC-PAIX01 / 02 11
5.4. Analog Input – CC-PAIN01 13
5.5. Low Level Analog (Temperature) Input – LLMUX – CC-PAIM01 14
5.6. Low Level Analog (Temperature) Input – CC-PAIL51 17
5.7. Pulse Input – CC-PPIX01 19
5.8. Analog Output with HART – CC-PAOH01 21
5.9. Analog Output with HART – CC-PAOH51 23
5.10. Analog Output – CC-PAOX01 25
5.11. Analog Output – CC-PAON01 27
5.12. Digital Input 24VDC – CC-PDIL01 29
5.13. Digital Input 24VDC – CC-PDIL51 30
5.14. Digital Input Sequence of Events – CC-PDIS01 31
5.15. Digital Input High Voltage- CC-PDIH01 33
5.16. Digital Output - Bussed 24VDC – CC-PDOB01 34
5.17. Digital Output – Relay IOTA – Uses CC-PDOB01 IOM 36
5.18. Digital Output – SINKTYPE 24VDC – CC-PDOD51 38
5.19. Universal Input Output – CC-PUIO01 39
5.20. Universal Input Output – CC-PUIO31 44
6. Function Matrix 49

1. Product Introduction Summary

1.1. Overview

This document provides technical information to configure the Experion® Series C I/O and the C300 Controller, released starting with Experion R300.

1.2. Scope

The following Series C I/O items are included in this document.

- Digital Input 24 VDC
- Digital Input 110 VAC / 125VDC
- Digital Input 220 VAC
- Digital Output (24 VDC bussed)
- Digital Output Relay
- High Level Analog Input with HART
- High Level Analog Input without HART
- Analog Output with HART
- Analog Output without HART
- Low Level Multiplexer – RTD & TC
- Low Level Input – RTD & TC
- Pulse Input
- Universal Input Output


1.3. Definitions

- **Input Output Termination Assembly (IOTA):** An assembly that holds the IOM and the connections for field wiring,
- **Input Output Module (IOM):** A device that contains most of the electronics required to perform a specific I/O function. The IOM plugs onto the IOTA.

2. Features

All Series C components feature an innovative design that supports enhanced heat management. This unique look provides a significant reduction in overall size for the equivalent function.

The unique features of Series C I/O include:



- I/O Module and field terminations are combined in the same area. The I/O Module is plugged into the IOTA to eliminate the need for a separate chassis to hold the electronics assemblies.
- Two level “detachable” terminals for landing the field wiring in the enclosure, providing easier plant installation and maintenance.
- Field power is supplied through the IOTA, with no need for extra power supplies and the associated craft wired marshalling.
- Redundancy is available directly on the IOTA without any external cabling or redundancy control devices, by simply adding a second IOM to an IOTA.
- The Series C innovative styling is one of its unique features. This styling includes features to facilitate the effective use of control hardware in a systems environment. These features include:
- Vertical mounting for more effective wiring since most field wiring applications require entry from the top or bottom of the systems cabinet.
- An “information circle” for a quick visual cue to draw the Maintenance Technician’s eye to important status information.
- “Tilted” design for effective heat management within the cabinet enclosure. Since Series C allows for a significant increase in cabinet density, an effective heat management system is critical for high systems availability.
- Input and output circuits are protected from shorts to alleviate the need for in-line fusing, reducing installation and maintenance costs.

4. I/O Module Sizes

IOTA Sizing is nominal (6in = 152mm, 9in =228mm, 12in =304mm, 18in = 457mm)I/O modules are associated with their respective IOTAs in the table below. An I/O Module is supported by one or more IOTAs.

I/O Module	IOTA	Description	Circuits	Size (in ")	Red.
CC-PAIH01		High-Level AI HART	16		√
	CC-TAIX01	AI IOTA		6	
	CC-TAIX11	AI IOTA Red		12	√
CC-PAIH02 CC-PAIX01 / 02		High-level AI HART High-level AI w/o HART	16		√
	CC-TAIX01	AI IOTA		6	
	CC-TAIX11	AI IOTA Red		12	√
	CC-TAID01	AI IOTA – 16 Channel Differential		9	
	CC-TAID11	AI IOTA Red – 16 Channel Differential		12	√
CC-PAIH51		High-level AI HART	16		√
	CC-TAIX51	AI IOTA		6	
	CC-TAIX61	AI IOTA Red		12	√
CC-PAIN01		High-level AI w/o HART	16		√
	CC-TAIN01	AI IOTA		6	
	CC-TAIN11	AI IOTA Red		12	√
CC-PPIX01		Pulse Input w/ Fast Cut-off	8		√
	CC-TPIX11	PI IOTA Red		12	√
CC-PAIM01		PMIO LL Mux	64		
	CC-TAIM01	PMIO LL Mux IOTA		6	
	FTA				
	Mx-TAMT04	LL Mux TC FTA	16	12	
	Mx-TAMT14	LL Mux TC FTA w/Remote CJR	16	12	
	Mx-TAMR04	LL Mux RTD FTA	16	12	
CC-PAIL51	CC-TAIL51	Low-level AI	16	9	
CC-PPIX01	CC-TPIX01	Pulse Input	8	12	√

Parameter	Specification
Maximum Open Circuit Voltage	22 V
Response Time (DAC input code to output)	settles to within 1% of final value within 80 ms
Gap (0 mA) of Output to Field on Switchover	10 ms maximum (applies to Redundancy only)