MANUFACTURER DOCUMENT PACKAGE

Manufacturer's Manual

Reference package for procurement and maintenance review

ABB

AI843

THERMOCOUPLE ANALOG INPUT MODULE

Used with the applicable S800 I/O configuration.

REFERENCE PACKAGE

OFFICIAL DOCUMENT

Selected official manufacturer pages follow this cover.

Source: ABB Compact Product Suite Catalog 3BSE062980; exact-model ABB hardware-selector specifications

S800 I/O Modules

Digital input modules	
DI810	16 channels, 2 groups of 8 channels, 24 V d.c., current sink.
DI811	16 channels, 2 groups of 8 channels, 48 V d.c., current sink.
DI814	16 channels, 2 groups of 8 channels, 24 V d.c., current source.
DI818	32 channels, 2 groups of 16 channels, 24 V d.c., current sink.
DI820	8 channels, separate returns, 110 V d.c., 120 V a.c.
DI821	8 channels, separate returns, 220 V d.c., 230 V a.c.
DI825	With time tagging, 8 channels, separate returns, 125 V d.c.
DI828	16 channels, separate returns, 110 V d.c., 120 V a.c / d.c.
DI830	With time tagging. 16 channels, 2 groups of 8 channels, 24 V d.c., current sink. Resolution: < 0.5 ms.
DI831	With time tagging. 16 channels, 2 groups of 8 channels, 48 V d.c., current sink. Resolution: < 0.5 ms.
Pulse input module	
DP820	2 channels, separate returns, 0.25 Hz - 1.5 MHz, signal voltage: 5 / 12 V d.c.
DP840	8 channels, extended diagnostics, wire-fault detection, current limited sensor supply, 0.5-20 kHz, 12/24 V d.c or NAMUR, common return.
Digital output modules	
DO810	16 channels, 2 groups of 8 channels, 24 V d.c., max 0.5 A d.c., transistor, current source, short-circuit-proof.
DO814	16 channels, 2 groups of 8 channels, 24 V d.c., max 0.5 A, transistor, current sink, short-circuit-proof.
DO815	8 channels, 2 groups of 4 channels, 24 V d.c., max 2 A, transistor, current source, short-circuit-proof, wire-fault detection.
DO818	32 channels, 2 groups of 16 channels, 24 V, max 0.5 A d.c., transistor, current source, short-circuit-proof
DO820	8 channels, separate returns, 5-250 V, max 3 A a.c./d.c., relay (N.O.).
DO821	8 channels, separate returns, 5-250 V, max 3 A a.c./d.c., relay (N.C.).
DO828	16 channels, separate returns, 5-250V a.c. / 5-125V d.c. max 2A a.c./d.c., relay (N.O.).
Analog input modules	
AI810	8 channels, single-ended, 0(4)-20 mA, 0(2)-10 V, 12 bits.
AI815	8 channels with HART. 0(4)..20 mA, 0(1)..5 V, 12 bit, single ended, current limited transmitter supply.
AI820	Differential inputs, 4 channels, 0(1)-5 V, ±0(2)-10 V, ±0(4)-20 mA, 14 bits + sign.
AI825	Individually galvanically isolated channels, 4 channels, ±0(2)-10 V, ±0(4)- 20 mA, 14 bits + sign.
AI830A	RTD inputs, 8 channels, Pt100, Ni100, Ni120, Cu10, resistor 0-400 ohms, 14 bits, 3-wire.
AI835A	TC inputs, 8 channels, (7+ ref. junction), separate returns. TC types B, C, D, E, J, K, L, N, R, S, T, U, - 30…75 mV, 15 bits.
Analog output modules	
AO810V2	8 channels, common return, 0(4)-20 mA, 14 bits, load: 850 ohms (short-circuit-proof).
AO815	8 channels with HART. 4..20 mA, 12 bit, load: 750 ohms, common return, short-circuit-proof.
AO820	4 channels, individually galvanically isolated, separate returns, measuring range: ±0(2)-10 V, ±0(4)-20 mA, resolution: 12 bits + sign, load: 500 ohms (current) / 5 kohms (voltage), short-circuit-proof.
Intrinsic-safety modules	
DI890	8 channels, separate returns, proximity sensors (NAMUR) or voltage-free contact., current sink, wire-fault detection.
DO890	4 channels, separate returns, load 150-5000 ohms, 11 V @ 40 mA, current source, wire-fault detection, short circuit-proof.
AI890	8 channels, single-ended, 0(4)-20 mA, 12 bits, transmitter power supply.
AI893	8 channels, TC: 7 + ref. junction, sep. returns. TC types B, C, E, J, K, L, N, R, S, T, U, -10…80 mV. RTD: Pt50-1000, Ni100-500, Cu10-100, resistor 0-4000 W, 3-wire. 15 bits + sign.
AI895	8 channels, single-ended, 4-20 mA, 12 bits, transmitter power supply, HART pass-through.
AO890	8 channels, common return, 0(4)-20 mA, 12 bits, load: 725 ohms short-circuit-proof.
AO895	8 channels, common return, 4-20 mA, 12 bits, load: 725 ohms short-circuit-proof, HART pass-through.
Redundant modules	
DI840	16 channels, common return, 24 V d.c., current sink, extended diagnostics, time-tagging, current limited sensor supply.
DP840	8 channels, common return, 0.5-20 kHz, 12/24 V d.c or NAMUR, extended diagnostics, wire-fault detection.
DO840	16 channels, common return, 24 V d.c., max. 0,5 A, transistor, current source, short-circuit-proof, extended diagnostics.
AI843	TC input, 8 channels + ref. junction. TC types: B, C, E, J, K, L, N, R, S, T, U, -30…75 mV, 16 bits, extended diagnostics.
AI845	8 channels, 12 bits, 0(4)-20 mA 0(1)-5 V, extended diagnostics, HART pass-through, current limited transmitter supply, single ended.
Redundant modules - HI Integrity	
AI880A	8 channels with HART, 0(4)-20 mA, 12 bits, SIL3, current limited transmitter power.
DI880	16 channels, 24V d.c, SIL3, current limited sensor power, time-tagging.
DO880	16 channel, 24 V d.c., 0.5 A, SIL3, Current sourcing, current limiting

S800 I/O modules selection guide

	NAMUR inputs	Binary 24 V	Binary 48 V	Binary 110 V	Binary 230 V	Binary Relay	Analog Unipolar	Analog Bipolar	Temperature RTD	Temperature T/C	SOE	HART	Intrinsic safety	Redundant	High integrity
I/O Features S800															
Digital input modules															
DI810		•													
DI811			•												
DI814		•													
DI818		•													
DI820				•											
DI821					•										
DI825				•							•				
DI828				•											
DI830		•									•				
DI831			•								•				
DI840		•									•			•	
DI880		•									•			•	•
DI890	•												•		
Digital output modules															
DO810		•													
DO814		•													
DO815		•													
DO818		•													
DO820						•									
DO821						•									
DO828						•									
DO840		•												•	
DO880		•												•	•
DO890													•		
Pulse input modules															
DP820		•													
DP840	•	•												•	
Analog input modules															
AI810							•								
AI815							•					•			
AI820								•							
AI825								•							
AI830A									•						
AI835A										•					
AI843										•				•	
AI845							•					•		•	
AI880A							•					•		•	•
AI890							•						•		
AI893									•	•			•		
AI895							•					•	•		
Analog output modules															
AO810V2							•								
AO815							•					•			
AO820								•							
AO845A							•					•		•	
AO890							•						•		
AO895							•					•	•		
S800L modules															
DI801		•													
DI802				•											
DI803					•										
DO801		•													
DO802						•									
AI801							•								
AO801							•								

Communication

Upgrade Kit and Tool Cables

Upgrade Kit and Tool Cables		Article no.	
	**TK212A Tool cable RJ45 8P8C plug** Used to connect a PC to CI801, CI840 or CI840A for download of software. Download to CI801 requires a TK527V030 in addition. RJ45 (male) to Dsub-9 (female), length 3 m. RJ45 8P8C plug (with shell). Cable : UL2464 26 AWG x 8C.	3BSC630197R1	
	**FS801K01 Service adapter kit** Including: • 1 pcs Service adapter FS801 • 1 pcs cable TK802 For connection of CI801 to PC a cable TK212A, is also needed.	3BSE038407R1	

S800 I/O

S800 I/O Modules

Analog Input Modules		Article no.	
	**AI810 Analog input 8 ch.** 0(4)..20mA, 0..10V, 12Bit, single ended. Use Module Termination Unit TU810, TU812, TU814, TU818, TU830, TU833, TU835, TU838, TU850.	3BSE008516R1	
	AI815 Analog Input HART 8 ch. 0(4)..20mA, 0(1)..5V, 12bit, single ended. Current limited transmitter power distribution. Use Module Termination Unit TU810, TU812, TU814, TU818, TU830, TU833, TU835, TU838.	3BSE052604R1	
	AI820 Analog input 4 ch. +-20mA, 0(4)...20mA, +-10V, +-5V, 0(1)...5V, diff., 50V CMV,. Rin(curr)250 Ohms, 14bit + sign. Individually galvanic isolated channels. Use Module Termination Unit TU810, TU812, TU814, TU830, TU833.	3BSE008544R1	
	AI825 Analog Input 4 ch. -20..20mA, -10..10V, 14bit + sign. Individually galvanic isolated channels. Use Module Termination Unit TU811, TU813, TU831.	3BSE036456R1	
	AI830A Analog input RTD 8 ch. Pt100, Ni100/120, Cu10, R. Use Module Termination Unit TU810, TU812, TU814, TU830, TU833.	3BSE040662R1	
	AI835A Thermocouple/mV Input 8 ch. Use Module Termination Unit TU810, TU812, TU814, TU818, TU830, TU833.	3BSE051306R1	
	AI843 Termocouple/mV Input S/R 8 ch. Single or redundant. 16bit. Use Module Termination Unit TU818, TU830, TU833, TU842, TU843, TU852.	3BSE028925R1	