

OFFICIAL MANUFACTURER DOCUMENT PACKAGE

Manufacturer's Manual

6ES7318-2AJ00-0AB0

Siemens official documentation for the exact article number.

Source: 6ES7318-2AJ00-0AB0.pdf

Selected official Siemens pages follow this cover.

*** SPARE PART*** SIMATIC S7-300, CPU 318-2 DP 512 KBYTE
USER MEMORY (256 KB CODE; 256 KB DATA 1ST INTERF. = MPI
12 MBIT/S; 2ND INTERF. = PROFIBUS DP



General information	
Hardware product version	03
Firmware version	V3.0
Engineering with	
• Programming package	STEP 7 V5.1 SP2
Supply voltage	
Rated value (DC)	Yes
• 24 V DC	
permissible range, lower limit (DC)	20.4 V
permissible range, upper limit (DC)	28.8 V
external protection for power supply lines (recommendation)	Miniature circuit breaker; 2 A, type B or C
Input current	
Current consumption (in no-load operation), typ.	1.2 A
Inrush current, typ.	8 A
I^2t	0.4 A ² ·s
Power loss	
Power loss, typ.	12 W

Memory	
Work memory	
• integrated	512 kbyte
Load memory	
• expandable FEPRM	Yes
• expandable FEPRM, max.	4 Mbyte
• integrated RAM, max.	64 kbyte
• expandable RAM	Yes
• expandable RAM, max.	2 Mbyte
Backup	
• present	Yes
• with battery	Yes; all blocks
• without battery	Yes; 11 KB
CPU processing times	
for bit operations, typ.	0.1 μ s
for bit operations, max.	0.1 μ s
for word operations, typ.	0.1 μ s
for fixed point arithmetic, typ.	0.1 μ s
for floating point arithmetic, typ.	0.6 μ s
for timer/counter operations, typ.	0.1 μ s
CPU-blocks	
DB	
• Number, max.	2 047; Number band: 1 to 2047
• Size, max.	64 kbyte
FB	
• Number, max.	1 024; Number band: 0 to 1023
• Size, max.	64 kbyte
FC	
• Number, max.	1 024; Number band: 0 to 1023
• Size, max.	64 kbyte
OB	
• Description	see instruction list
• Number, max.	see instruction list
• Size, max.	64 kbyte
• Number of time alarm OBs	2; OB 10, 11
• Number of delay alarm OBs	2; OB 20, 21
• Number of cyclic interrupt OBs	2; OB 32, 35
• Number of process alarm OBs	2; OB 40, 41
• Number of startup OBs	1; OB 100
• Number of asynchronous error OBs	5; OB 80, 81, 85, 86, 87
• Number of synchronous error OBs	2; OB 121, 122

Nesting depth	
• per priority class	16
• additional within an error OB	3
Counters, timers and their retentivity	
S7 counter	
• Number	512
of which retentive without battery	
— can be set	Yes
— preset	Z 0 to Z 7
Counting range	
— lower limit	0
— upper limit	999
IEC counter	
• present	Yes
• Type	SFB
S7 times	
• Number	512
Retentivity	
— adjustable	Yes
— preset	No times retentive
Time range	
— lower limit	10 ms
— upper limit	9 990 s
IEC timer	
• present	Yes
• Type	SFB
Data areas and their retentivity	
Flag	
• Number, max.	1 024 byte
• Retentivity available	Yes; MB 0 to MB 1023
• Retentivity preset	MB 0 to MB 15
• Number of clock memories	8; 1 memory byte
Data blocks	
• Number, max.	2 047; from DB 1 to DB 2047
• Size, max.	64 kbyte
Local data	
• adjustable, max.	8 192 byte
• preset	3 584 byte
• per priority class, max.	8 192 byte
Address area	

I/O address area	
• Inputs	8 kbyte
• Outputs	8 kbyte
of which distributed	
— Inputs	8 kbyte
— Outputs	8 kbyte
Process image	
• Inputs	2 048 byte
• Outputs	2 048 byte
• Inputs, default	256 byte
• Outputs, default	256 byte
Digital channels	
• Inputs	65 536
— of which central	1 024
• Outputs	65 536
— of which central	1 024
Analog channels	
• Inputs	4 096
— of which central	256
• Outputs	4 096
— of which central	128
Hardware configuration	
Number of expansion units, max.	3
Number of DP masters	
• integrated	2
• via CP	4; CP 342-5
Number of operable FMs and CPs (recommended)	
• FM	16
• CP, PtP	8
• CP, LAN	16
Rack	
• Racks, max.	4
• Modules per rack, max.	8
Time of day	
Clock	
• Hardware clock (real-time)	Yes
• retentive and synchronizable	Yes
• Deviation per day, max.	10 s
Operating hours counter	
• Number	8
• Number/Number range	0 to 7