MANUFACTURER DOCUMENT PACKAGE

Manufacturer's Manual

Reference package for procurement and maintenance review

ALLEN-BRADLEY

1756-L62S

GUARDLOGIX SAFETY CONTROLLER

Used with the applicable Allen-Bradley ControlLogix configuration.

REFERENCE PACKAGE

OFFICIAL DOCUMENT

Selected official manufacturer pages follow this cover.

Source: Rockwell Automation manufacturer documentation

Environmental Specifications - 1756-L7*x* ControlLogix Controllers

Attribute	1756-L72, 1756-L73, 1756-L74, 1756-L75
Temperature, operating IEC 60068-2-1 (Test Ad, Operating Cold), IEC 60068-2-2 (Test Bd, Operating Dry Heat), IEC 60068-2-14 (Test Nb, Operating Thermal Shock)	0…60 °C (32…140 °F)
Temperature, storage IEC 60068-2-1 (Test Ab, Unpackaged Nonoperating Cold), IEC 60068-2-2 (Test Bb, Unpackaged Nonoperating Dry Heat), IEC 60068-2-14 (Test Na, Unpackaged Nonoperating Thermal Shock)	-40…85 °C (-40…185 °F)
Relative humidity IEC 60068-2-30 (Test Db, Unpackaged Damp Heat)	5…95% noncondensing
Vibration IEC 60068-2-6 (Test Fc, Operating)	2 g @ 10…500 Hz
Shock, operating IEC 60068-2-27 (Test Ea, Unpackaged Shock)	30 g
Shock, nonoperating IEC 60068-2-27 (Test Ea, Unpackaged Shock)	50 g (45 g with SD card installed)
Emissions CISPR 11	Group 1, Class A
ESD immunity IEC 61000-4-2	6 kV contact discharges 8 kV air discharges
Radiated RF immunity IEC 61000-4-3	10V/m with 1 kHz sine-wave 80% AM from 80…2000 MHz 10V/m with 200 Hz 50% Pulse 100% AM @ 900 MHz 10V/m with 200 Hz 50% Pulse 100% AM @ 1890 MHz 3V/m with 1 kHz sine-wave 80% AM from 2000…2700 MHz

Certifications - 1756-L7*x* ControlLogix Controllers

Certification[1]	1756-L72, 1756-L73, 1756-L74, 1756-L75
c-UL-us	UL Listed Industrial Control Equipment, certified for US and Canada. See UL File E65584. UL Listed for Class I, Division 2 Group A,B,C,D Hazardous Locations, certified for U.S. and Canada. See UL File E194810.
CE	European Union 2004/108/EC EMC Directive, compliant with: • EN 61326-1; Meas./Control/Lab., Industrial Requirements • EN 61000-6-2; Industrial Immunity • EN 61000-6-4; Industrial Emissions • EN 61131-2; Programmable Controllers (Clause 8, Zone A & B)
C-Tick	Australian Radiocommunications Act, compliant with: AS/NZS CISPR 11; Industrial Emissions
Ex	European Union 94/9/EC ATEX Directive, compliant with: • EN 60079-15; Potentially Explosive Atmospheres, Protection 'n' • EN 60079-0; General Requirements • II 3 G Ex nA IIC T5X

(1) When marked. See the Product Certification link at http://www.ab.com for Declarations of Conformity, Certificates, and other certification details.

1756 GuardLogix Controllers



A GuardLogix controller is a ControlLogix controller that also provides safety control. The GuardLogix system is a dual controller solution—you must use a 1756-L6*x*S primary controller and a 1756-LSP safety partner to achieve SIL 3/CAT. 4. A major benefit of this system is that it's still a single project, safety and standard together. The safety partner controller is a part of the system, is automatically configured, and requires no user setup.

During development, safety and standard have the same rules, multiple programmers, online editing, and forcing are all allowed. Once the project is tested and ready for final validation, you set the Safety Task to a SIL 3 integrity level, which is then enforced by the GuardLogix controller. When safety memory is locked and protected, the safety logic can't be modified and all safety functions operate with SIL 3 integrity. On the standard side of the GuardLogix controller, all functions operate like a regular Logix controller. Thus online editing, forcing, and other activities are all allowed.

With this level of integration, safety memory can be read by standard logic and external devices, like HMIs or other controllers, eliminating the need to condition safety memory for use elsewhere. The result is easy system-wide integration and the ability to display safety status on displays or marquees. Use Guard I/O modules for field device connectivity on Ethernet or DeviceNet networks, and for safety interlocking between GuardLogix controllers use Ethernet or ControlNet networks. Multiple GuardLogix controllers can share safety data for zone to zone interlocking, or a single GuardLogix controller can use remote distributed safety I/O between different cells/areas.

In addition to the standard features of a ControlLogix controller, the GuardLogix controller has these safety-related features.

Features - GuardLogix Controllers

Feature	1756-L61S, 1756-L62S, 1756-L63S, 1756-LSP
Safety communication options	Standard and safety • EtherNet/IP • ControlNet • DeviceNet
Network connections, per network module	• 100 ControlNet (1756-CN2/A) • 40 ControlNet (1756-CNB) • 256 EtherNet/IP; 128 TCP (1756-EN2*x*) • 128 EtherNet/IP; 64 TCP (1756-ENBT)
Controller redundancy	Not supported
Programming languages	Relay ladder

Technical Specifications - 1756 GuardLogix Controllers

Attribute	1756-L61S	1756-L62S	1756-L63S	1756-LSP
User memory	2 MB	4 MB	8 MB	—
Safety memory	1 MB	1 MB	3.75 MB	—
I/O memory	478 KB			—
Optional flash memory[1]	64 MB (cat. no. 1784-CF64) 128 MB (cat. no. 1784-CF128)			—
Digital I/O, max	128,000			—
Analog I/O, max	4000			—
Total I/O, max	128,000			—
Replacement battery	1756-BA2			
Current draw @ 5.1V DC	1200 mA			
Current draw @ 24V DC	14 mA			
Power dissipation	3.5 W			
Thermal dissipation	11.9 BTU/hr			
Isolation voltage	30V (continuous), Basic Insulation Type, RS-232 to system Type tested at 720V DC for 60 s			
Serial cables	1756-CP3 or 1747-CP3, right angle connector to controller, straight to serial port, 3 m (9.84 ft)			
Weight, approx.	0.32 kg (0.70 lb)			
Slot width	1			
Module location	Chassis-based, any slot			
Chassis	1756-A4, 1756-A7, 1756-A10, 1756-A13, 1756-A17			
Power supply, standard	1756-PA72/C, 1756-PA75/B, 1756-PB72/C, 1756-PB75/B, 1756-PC75/B, 1756-PH75/B			
Power supply, redundant	1756-PA75R, 1756-PB75R, 1756-PSCA2			
Wire category	2 - on communication ports[2]			
North American temperature code	T4A			
Enclosure type rating	None (open-style)			

(1) The GuardLogix controller does not support user program storage or retrieval by using a CompactFlash card.

(2) Use this conductor category information for planning conductor routing as described in the system level installation manual. See the Industrial Automation Wiring and Grounding Guidelines, publication 1770-4.1.