MANUFACTURER DOCUMENT PACKAGE

Manufacturer's Manual

Selected official pages for procurement and maintenance review

PRODUCT BRAND

Siemens

PRODUCT MODEL

6ES7521-1BL10-0AA0

DI 32x24VDC BA Input Module. Source PDF pages: M1 pp. 3,10,20-22. Adjacent model text on shared pages is outside this product reference.

OFFICIAL SOURCE

Digital input module DI 32x24VDC BA (6ES7521-1BL10-0AA0); 09/2014

Siemens original documentation and product reference

Siemens 09/2014 product-reference excerpt, not complete installation instructions. Negative input voltage: -3 V continuously; -30 V for brief reverse-polarity protection only.

AMIKON PRODUCT SUPPORT

+86-18020776786 INFO@AMIKON.CN

AMIKONG.COM

Amikon Limited prepared this independent reference package. Selected manufacturer pages follow with their original content and pagination visible.

Legal information

Warning notice system

This manual contains notices you have to observe in order to ensure your personal safety, as well as to prevent damage to property. The notices referring to your personal safety are highlighted in the manual by a safety alert symbol, notices referring only to property damage have no safety alert symbol. These notices shown below are graded according to the degree of danger.

⚠ DANGER

indicates that death or severe personal injury **will** result if proper precautions are not taken.

⚠ WARNING

indicates that death or severe personal injury **may** result if proper precautions are not taken.

⚠ CAUTION

indicates that minor personal injury can result if proper precautions are not taken.

NOTICE

indicates that property damage can result if proper precautions are not taken.

If more than one degree of danger is present, the warning notice representing the highest degree of danger will be used. A notice warning of injury to persons with a safety alert symbol may also include a warning relating to property damage.

Qualified Personnel

The product/system described in this documentation may be operated only by **personnel qualified** for the specific task in accordance with the relevant documentation, in particular its warning notices and safety instructions. Qualified personnel are those who, based on their training and experience, are capable of identifying risks and avoiding potential hazards when working with these products/systems.

Proper use of Siemens products

Note the following:

⚠ WARNING

Siemens products may only be used for the applications described in the catalog and in the relevant technical documentation. If products and components from other manufacturers are used, these must be recommended or approved by Siemens. Proper transport, storage, installation, assembly, commissioning, operation and maintenance are required to ensure that the products operate safely and without any problems. The permissible ambient conditions must be complied with. The information in the relevant documentation must be observed.

Trademarks

All names identified by ® are registered trademarks of Siemens AG. The remaining trademarks in this publication may be trademarks whose use by third parties for their own purposes could violate the rights of the owner.

Disclaimer of Liability

We have reviewed the contents of this publication to ensure consistency with the hardware and software described. Since variance cannot be precluded entirely, we cannot guarantee full consistency. However, the information in this publication is reviewed regularly and any necessary corrections are included in subsequent editions.

Siemens AG
Industry Sector
Postfach 48 48
90026 NÜRNBERG
GERMANY

A5E32363711-AB
℗ 09/2014 Subject to change

Copyright © Siemens AG 2014.
All rights reserved

Properties

The module has the following technical properties:

- 32 digital inputs; electrically isolated in groups of 16
- Rated input voltage 24 VDC
- Suitable for switches and 2-/3-/4-wire proximity switches
- Hardware compatible with digital input module DI 16x24VDC BA (6ES7521-1BH10-0AA0)

The module supports the following functions:

Table 2- 1 Version dependencies of the module functions

Function	Firmware version of the module	Configuration software	
		STEP 7 (TIA Portal)	GSD file in STEP 7 (TIA Portal) V12 or higher, or STEP 7 V5.5 SP3 or higher
Firmware update	V1.0.0 or higher	V13 or higher	X
Identification data I&M0 to I&M3	V1.0.0 or higher	V13 or higher	X
Module internal shared input (MSI)	V1.0.0 or higher	V13 Update 3 or higher (PROFINET IO only)	X (PROFINET IO only)
Configurable submodules / submodules for Shared Device	V1.0.0 or higher	V13 Update 3 or higher (PROFINET IO only)	X (PROFINET IO only)

You can configure the module with STEP 7 (TIA Portal) and with a GSD file.

Accessories

The following accessories are supplied with the module and can also be ordered separately as spare parts:

- Front connector (push-in terminals) including cable tie
- Labeling strips
- U connector
- Universal front door

You can find more information on accessories in the S7-1500 Automation System (http://support.automation.siemens.com/WW/view/en/59191792) system manual and the ET 200MP Distributed I/O System (http://support.automation.siemens.com/WW/view/en/59193214) system manual.

Technical specifications

6

Technical specifications of the DI 32x24VDC BA

	6ES7521-1BL10-0AA0
Product type designation	DI 32x24VDC BA
General information	
Hardware version	E01
Firmware version	V1.0.0
Product function	
I&M data	Yes; I&M0 to I&M3
Engineering with	
STEP 7 TIA Portal can be configured/integrated as of version	V13 / V13
STEP 7 can be configured/integrated as of version	V5.5 SP3 / -
Operating mode	
MSI	Yes
Supply voltage	
Type of supply voltage	DC
Rated value (DC)	24 V
Permitted range, low limit (DC)	20.4 V
Permitted range, high limit (DC)	28.8 V
Power	
Power taken from the backplane bus	1.05 W
Power loss	
Power loss, typ.	3 W
Digital inputs	
Number of inputs	32
Sinking/sourcing input	Sinking input
Input characteristic curve acc. to IEC 61131, type 3	Yes
Input voltage	
Rated value, DC	24
for signal "0"	-30 to +5 V
for signal "1"	11 to 30 V
Permitted voltage at input, min.	-30 V; -3 V permanently; -30 V brief reverse polarity protection
Permitted voltage at input, max.	30 V
Input current	
for signal "1", typ.	2.7 mA

	6ES7521-1BL10-0AA0
Input delay (for rated value of input voltage)	
For standard inputs	
• Configurable	No
• with "0" to "1", min.	3 ms
• with "0" to "1", max.	4 ms
• with "1" to "0", min.	3 ms
• with "1" to "0", max.	4 ms
For interrupt inputs	
• Configurable	No
Cable length	
Cable length shielded, max.	1000 m
Cable length unshielded, max.	600 m
Encoders	
Connectable encoders	
2-wire sensor	Yes
• Permitted quiescent current (2-wire sensor), max.	1.5 mA
Isochronous mode	
Isochronous mode (application synchronized up to terminal)	No
Interrupts/diagnostics/status information	
Interrupts	
Diagnostics interrupt	No
Hardware interrupt	No
Diagnostics alarms	
Diagnostics	No
Monitoring of the supply voltage	No
Wire break	No
Short-circuit	No
Fuse blown	No
Diagnostics indicator LED	
RUN LED	Yes; green LED
ERROR LED	Yes; red LED
MAINT LED	No
Monitoring of the supply voltage	No
Channel status display	Yes; green LED
For channel diagnostics	No
For module diagnostics	No

	6ES7521-1BL10-0AA0
Electrical isolation	
Electrical isolation of channels	
Between the channels	No
Between the channels, in groups of	16
Between the channels and the backplane bus	Yes
Between the channels and the supply voltage of the electronics	No
Permitted potential difference	
Between different circuits	75 VDC / 60 VAC (basic isolation)
Isolation	
Isolation tested with	707 VDC (type test)
Distributed mode	
Prioritized startup	Yes
Dimensions	
Width	25 mm
Height	147 mm
Depth	129 mm
Weights	
Weight, approx.	260 g
Miscellaneous	
Note:	Supplied incl. 40-pin push-in front connector