

applications & TOOLS

**Operating a MASTERDRIVES braking unit with a
MICROMASTER 440 FX / GX**

SIEMENS

Application description
MICROMASTER 440

Operating a MASTERDRIVES braking unit with a MICROMASTER ID-No: 22093967
440 FX / GX

Note

The Application Examples are not binding and do not claim to be complete regarding the circuits shown, equipping and any eventuality. The Application Examples do not represent customer-specific solutions. They are only intended to provide support for typical applications. You are responsible in ensuring that the described products are correctly used. These Application Examples do not relieve you of the responsibility in safely and professionally using, installing, operating and servicing equipment. When using these Application Examples, you recognize that Siemens cannot be made liable for any damage/claims beyond the liability clause described. We reserve the right to make changes to these Application Examples at any time without prior notice. If there are any deviations between the recommendations provided in these Application Examples and other Siemens publications - e.g. Catalogs - then the contents of the other documents have priority.

Warranty, liability and support

We do not accept any liability for the information contained in this document.

Any claims against us - based on whatever legal reason - resulting from the use of the examples, information, programs, engineering and performance data etc., described in this Application Examples shall be excluded. Such an exclusion shall not apply in the case of mandatory liability, e.g. under the German Product Liability Act ("Produkthaftungsgesetz"), in case of intent, gross negligence, or injury of life, body or health, guarantee for the quality of a product, fraudulent concealment of a deficiency or breach of a condition which goes to the root of the contract ("wesentliche Vertragspflichten"). However, claims arising from a breach of a condition which goes to the root of the contract shall be limited to the foreseeable damage which is intrinsic to the contract, unless caused by intent or gross negligence or based on mandatory liability for injury of life, body or health. The above provisions do not imply a change in the burden of proof to your detriment.

Copyright© 2006 Siemens A&D. It is not permissible to transfer or copy these Application Examples or excerpts of them without first having prior authorization from Siemens A&D in writing.

If you have any recommendations relating to this document then please send them to us at the following e-mail address:

<mailto:sdsupport.aud@siemens.com>

Operating a MASTERDRIVES braking unit with a MICROMASTER 440 FX / GX ID-No: 22093967

Preposition

Aim of the application

This application describes the possibility of using a MASTERDRIVE brake unit on a MICROMASTER 440 for safety-relevant regenerative operation (braking) of the motor.

Scope

This application shows how to determine the required brake unit, calculate the load duty cycle and explains how to mount and engineer the brake unit

Exclusion

This application does not include any description on how to engineer and commission the drive inverter.

It is assumed that the reader has the appropriate level of know-how about these subjects.

Reference to the Automation and Drives Service & Support

This article is from the Internet Application Portal of the Automation and Drives Service & Support. You can go directly to the download page of this document using this link.

<http://support.automation.siemens.com/WW/view/en/22093967>

Table of Contents

Table of Contents	4
Application description.....	5
1 Determining the braking module and braking resistor required.....	5
1.1 Defining the power data.....	6
1.2 Braking power for a periodic load duty cycle	7
1.3 Braking power for sporadic braking operations and when stopping the drive... 8	
1.3.1 Calculating the braking torque M _{brake} (in Nm):	8
1.3.2 Calculating the max. braking power P _{brake, max} (in kW):	8
1.3.3 Calculating the average braking power P _{brake, average} (in kW):.....	8
2 Selection and ordering data	9
3 Additional engineering information and instructions	10
3.1 Connecting and fusing the braking module	10
3.2 Information regarding the DC link capacitors in the braking module	11
3.3 Maximum cable lengths	11
3.4 Mounting the braking module and braking resistor.....	11
3.5 Monitoring the braking module and the braking resistor	11
3.6 Acknowledging and inhibiting the braking module	12
3.7 Response threshold of the braking module	12
3.8 Parameter setting on the MM440	12
3.9 Maximum permissible braking power	12
3.9.1 Engineering information.....	12
Appendix and references.....	13
4 References	13
4.1 Reference data	13
4.2 Internet link data	13
4.3 History.....	13

Application description

Introduction

For several drive applications, the motor can go into the regenerative mode (braking mode) for certain operating states.

Examples for these types of applications include:

- Cranes,
- Traversing drives,
- Conveyor belts, where the load on the belt moves the belt downwards,
- Dynamic traversing drives,
- Generally - drives with high moments of inertia, if the speed setpoint must be quickly reduced or the load braked.

When the motor is in the regenerative mode, the braking energy of the motor is fed back into the drive converter DC link via the inverter. This means that the DC link voltage increases. If a braking chopper and braking resistor are used, from a specific value of the DC link voltage, the braking energy is pulsed into the braking resistor. This therefore limits the DC link voltage.

For MM440, drive units, Sizes A to F have an integrated braking chopper. For braking operation, only an external braking resistor has to be connected to terminals B+/DC+ and B-.

Drive units, Sizes FX and GX do not have an integrated braking chopper. Braking operation can only be implemented using an external braking module and an external braking resistor. Components from the MASTERDRIVES range are used to implement this function.

The engineering and dimensioning of braking modules and braking resistors for MM440 in the power range from 90 to 200kW (CT) will be discussed in the following. It is assumed that the braking module is only connected to a single drive inverter and there is no DC link coupling between several drive inverters.

1 Determining the braking module and braking resistor required

MASTERDRIVES braking modules are available in the power range from 5 to 170kW; braking modules from 5 to 20kW include an internal braking resistor. The load capability of the internal braking resistors of the MASTERDRIVES braking modules in relationship to the power of the MM440 in Sizes FX and GX is extremely low. This is the reason that only braking resistors which can be externally connected are considered.

Operating a MASTERDRIVES braking unit with a MICROMASTER 440 FX / GX ID-No: 22093967

It is possible to connect several parallel braking modules to an AC drive inverter to increase the braking power. However, the power rating of the braking modules connected in parallel may only be a maximum of one power stage of the braking module.

If several braking modules are connected in parallel, every braking module must have its own assigned braking resistor.

1.1 Defining the power data

The power data of MasterDrives braking modules and braking resistors are specified for a load duty cycle of 90s.

The "P20" power is the possible braking power for a duration of 20s for a load duty cycle of 90s.

The peak braking power "P3" can be fully utilized for 3s and then for 20s but linearly decreasing.

The "PDB" power is the max. permissible continuous braking power.




Figure 1-1 Load diagram of the braking module with external braking resistor

Furthermore, the powers are applicable for a response threshold of the braking module of 774V DC (factory setting). The permissible braking powers are reduced if the response threshold is reduced (refer to Section 4.7).

A differentiation is made between 2 different load situations

Operating a MASTERDRIVES braking unit with a MICROMASTER 440 FX / GX ID-No: 22093967

1.2 Braking power for a periodic load duty cycle

For an actual load duty cycle duration = 90s, the following procedure can be applied:

- Determine the braking power which occurs within the load duty cycle $P_{\text{brake}} = f(t)$.
- Calculate the average value P_{brake} , average of the braking power within the load duty cycle.
- Select a braking module, whose P20 power is at least 400% higher than the average value of the braking power which has been determined.
- ($\Rightarrow P_{20} = 4 \cdot P_{\text{brake, average}}$)
- Check the peak braking power. In this case, the max. occurring braking power $P_{\text{brake, max}}$ in the load duty cycle may not exceed 150% of the P20 power of the selected braking module. If the peak braking power is greater than 150% of the P20 power, then the larger braking unit must be selected until this particular condition is fulfilled.
- ($\Rightarrow P_{\text{brake, max}} = 1.5 \cdot P_{20}$)

For an actual **load duty cycle duration = 90s**, the following procedure can be applied:

- Determine the braking power which occurs $P_{\text{brake}} = f(t)$.
- Select a time slice of 90s where the highest average value of the braking power occurs.
- Calculate the average value of the braking power P_{brake} , average within the selected 90s time slice.
- Select a braking module, whose P20 power is at least 400% higher than the average value of the braking power of the selected time slice.
- ($\Rightarrow P_{20} = 4 \cdot P_{\text{brake, average}}$)
- Check the peak braking power. In this case, the max. braking power which occurs at any instant in time (also outside the selected 90s time slice) may not be greater than 150% of the P20 power of the selected braking module. If the peak braking power exceeds 150% of the P20 power then a larger braking module should be selected until this condition is fulfilled.
- ($\Rightarrow P_{\text{brake, max}} = 1.5 \cdot P_{20}$)

The required braking module and the appropriately assigned braking resistor can be selected according to Table in Section 2.

Operating a MASTERDRIVES braking unit with a MICROMASTER 440 FX / GX ID-No: 22093967

1.3 Braking power for sporadic braking operations and when stopping the drive

The approach in this case is the same as for an actual load cycle duration = 90s (refer above).

The braking power occurring when a drive is stopped can be approximately calculated as follows:

1.3.1 Calculating the braking torque M_{brake} (in Nm):

$$M_{brake} = \frac{J_{tot} * n_{brake}}{9.55 * t_{brake}} \quad \text{whereby:}$$

J_{tot} = the total load moment of inertia plus the motor moment of inertia, referred to the motor shaft in (kg*m²)

n_{brake} = motor speed at the start of braking in (RPM)

t_{brake} = braking time until the motor comes to a standstill in (s)

1.3.2 Calculating the max. braking power $P_{brake, max}$ (in kW):

$$P_{brake, max} = \frac{M_{brake} * n_{brake}}{9550} * \eta_{mot} \quad \text{whereby:}$$

η_{mot} = motor efficiency in (percentage/100)

n_{brake} = motor speed at the start of braking in (RPM)

M_{brake} = braking torque in (Nm)

In this case the drive inverter efficiency has been neglected.

1.3.3 Calculating the average braking power $P_{brake, average}$ (in kW):

$$P_{brake, average} = \frac{1}{2} * P_{brake, max}$$

The power of the braking module can be determined using the average and maximum braking powers as described above (for an actual load duty cycle duration = 90s).

The required braking module and the assigned braking resistor can then be selected according to the Table in Section 3..

Operating a MASTERDRIVES braking unit with a MICROMASTER 440 FX / GX ID-No: 22093967

2 Selection and ordering data

The braking module and the assigned braking resistor can be determined according to the braking power, determined in Section 2., in the following Table.

The values apply for a 774V DC response threshold of the braking module (factory setting of the braking module).

Table 2-1 Selection and ordering data of the braking modules and braking resistors

Braking power			Braking module	Braking resistor			Fuses
P20	P3)	PDB	Order No.	Order No.	Resist- ance	Dimensions	Order No. (2 fuses are required)
(kW)	(kW)	(kW)			Ω	W x H x D	
5	7,5	1,25	6SE7018-0ES87-2DA1	6SE7018-0ES87-2DC0	80	540x180x145	3NE4101
10	15	2,5	6SE7021-6ES87-2DA1	6SE7021-6ES87-2DC0	40	540x360x145	3NE4101
20	30	5	6SE7023-2ES87-2DA1	6SE7023-2ES87-2DC0	20	485x485x305	3NE4102
50	75	12,5	6SE7028-0ES87-2DA1	6SE7028-0ES87-2DC0	8	740x480x305	3NE4121
100	150	25	6SE7031-6EB87-2DA1	6SE7031-6ES87-2DC0	4	605x740x485	3NE3225
170	255	42,5	6SE7032-7EB87-2DA1	6SE7032-7ES87-2DC0	2,35	1325x740x485	3NE3230-0B

3 Additional engineering information and instructions

3.1 Connecting and fusing the braking module

The connections between the MM440 drive inverter and the braking module must be kept as short as possible and routed so that they are ground-fault proof. The braking module is connected to terminals C/L+ and D/L- of the drive inverter (housing sizes FX and GX, refer to Section 2.4.2 of the MM440 Operating Instructions) (refer to Fig. 4-1 below). For braking modules with a P20 power of between 5 and 20kW, the internal resistor must be de-activated by removing the jumper between H1 and H2. Braking modules with ratings of between 50 and 200kW do not have an internal braking resistor.

If only one braking module is connected to the drive inverter and if the power of the drive inverter and braking module (P20 power) are approximately equal, then the braking module does not require any fuses. If the power difference is greater or if several braking modules are connected in parallel, then each braking module must be protected using 2 fuses (positive and negative branch) at the input.




Figure 3-1 Connecting the braking module to drive inverters MM440, FX and GX

Operating a MASTERDRIVES braking unit with a MICROMASTER 440 FX / GX ID-No: 22093967

3.2 Information regarding the DC link capacitors in the braking module

MASTERDRIVES braking modules include DC link capacitors. If the braking modules are commissioned after having been non-operational for more than 1 year, then these must be formed. Also refer to the information and instructions in the Operating Instructions (6SE7087-6CX87-2DA0).

MASTERDRIVES braking modules may not be connected to the DC link of the drive inverter which is under voltage (live) using a contactor.

3.3 Maximum cable lengths

The maximum cable lengths between the drive inverter and braking module may be 3m, and between the braking module and braking resistor, max. 15m.

3.4 Mounting the braking module and braking resistor

The braking module and braking resistor have degree of protection IP20. The braking module (this is 350mm deep) can be mounted in the electrical cabinet next to the drive inverter. The small braking resistors up to 10kW are suitable for wall and top assembly mounting (e.g. on the top of the cabinet); the larger braking modules are suitable for wall and floor mounting.

3.5 Monitoring the braking module and the braking resistor

The braking modules include a fault signaling relay which closes after the DC link has been charged. This relay opens when a fault occurs or an overtemperature condition. The braking resistors have an overtemperature contact which, in the normal state, is closed and is opened if there is an overtemperature condition.

Both of these contacts can be connected in series and incorporated in the fault circuit to open the main contactor at the drive inverter input. The reason for this is that the drive inverter must be isolated/disconnected from the line supply if the braking module develops a fault/overtemperature condition or if the braking resistor overheats. It must be carefully observed that before the main contactor is closed that the fault relay in the braking module is still open. This must be taken into consideration in the evaluation circuit so that the main contactor can close.

Operating a MASTERDRIVES braking unit with a MICROMASTER 440 FX / GX ID-No: 22093967

3.6 Acknowledging and inhibiting the braking module

If the braking module develops a fault condition, then this can be reset by entering a short acknowledgment pulse with a voltage of 24V DC at connections X38:1 (+) and X38:2 (-).

The braking module can be inhibited using a continuous signal at both terminals.

3.7 Response threshold of the braking module

When the DC link voltage increases when braking, the braking module is activated at a voltage of 774V (factory pre-setting). To reduce the voltage stressing on the motor insulation (e.g. when using third-party motors), the activation point of the braking module can be reduced to a response threshold of 673V (using switch S1 integrated in the braking module).

The response threshold can only be reduced to 673V for a line supply input voltage at the drive inverter of max. 3-ph. 400V AC +10%.

Further, the braking powers P3, P20 and PDB which can be achieved are reduced by 25% with respect to the values specified in Section 3.. This must be taken into account when selecting the braking module

3.8 Parameter setting on the MM440

When the external braking module is used with the MM440, the DC link voltage controller, which is used to limit the max. DC link voltage (VDC-max. controller) must be de-activated. To do this, parameter P1240 must be set from "1" to "0" at the MM440. If kinetic buffering is required, then parameter P1240 can be set to "2".

3.9 Maximum permissible braking power

In order to limit the ripple of the drive inverter DC link voltage, the ratio between the max. configured braking power P20, max of the braking module and the rated power of the drive inverter $P_{inverter}$ may not exceed 1.9. This is especially true when connecting braking modules in parallel.

(=> $P_{20, max} = 1.9 * P_{inverter}$)

3.9.1 Engineering information

Engineering a braking unit is explained in detail in the SINAMICS G150 Operating Instructions (Chapter 4.10.11). The power units (modules) of the MM4 Px and G150 are identical. This is the reason that this description can be used to design the braking unit.