



Power Supplies

VersaMax Power Supply modules snap onto any VersaMax CPU or Network Interface Unit or onto a power supply booster carrier. Each power supply can be used as the main power source for modules in the I/O station, or as a source of supplemental power for larger I/O applications.

| | IC200PWR102 | IC200PWR201 | IC200PWR202 | IC200PWB001 |
|-------------------------------|--|--|--|---|
| Product Name | 120/240 VAC Power Supply with Expanded 3.3 VDC | 12 VDC Power Supply | 12 VDC Power Supply with Expanded 3.3 VDC | VersaMax Power Supply Booster Carrier. Supplies power to all modules to the right of booster. Requires power supply. |
| Lifecycle Status | Active | Active | Active | Active |
| Input Voltage | 120/240 VAC | 9.6-15 VDC, 12 VDC nominal | 9.6-15 VDC, 12 VDC nominal | N/A |
| Output Voltage | 5 VDC, 3.3 VDC | 5 VDC, 3.3 VDC | 5 VDC, 3.3 VDC | N/A |
| Extended Power | Yes | No | Yes | N/A |
| Input Power | 27 VA | 11 W | 11 W | N/A |
| Isolated Power | N/A | No | No | N/A |
| Holdup Time | 20 ms | 10 ms | 10 ms | N/A |
| Inrush Current | N/A | 25 A at 12 VDC; 30 A at 15 VDC | 25 A at 12 VDC; 30 A at 15 VDC | N/A |
| Protection | Short circuit, overload | Short circuit, overload, reverse polarity | Short circuit, overload, reverse polarity | N/A |
| Total Output Current | 1.5 A maximum | 1.5 A maximum | 1.5 A maximum | N/A |
| 3.3V Output Current | 1.0 A maximum | 0.25 A maximum | 1.0 A maximum | N/A |
| 5V Output Current | 1.5 A minus the 3.3 V current used, maximum | 1.5 A minus the 3.3 V current used, maximum | 1.5 A minus the 3.3 V current used, maximum | N/A |
| Dimensions (W x H x D) | 49 mm (1.93 in) x 133.4 mm (5.25 in) x 39 mm (1.54 in), not including the height of the carrier or the DIN-rail | 49 mm (1.93 in) x 133.4 mm (5.25 in) x 39 mm (1.54 in), not including the height of the carrier or the DIN-rail | 49 mm (1.93 in) x 133.4 mm (5.25 in) x 39 mm (1.54 in), not including the height of the carrier or the DIN-rail | 66.8 mm (2.63 in) x 133.4 mm (5.25 in) x 70 mm (2.75 in), not including the height of DIN-rail |