

ALLEN-BRADLEY FLEX 5000

Product Data Sheet

5094-IF8

eight-channel analog input module

FUNCTION eight-channel analog input module	FAMILY Allen-Bradley FLEX 5000	ORIGIN Malaysia	WEIGHT 0.25 kg
---	-----------------------------------	--------------------	-------------------

Allen-Bradley FLEX 5000 5094-IF8 is a eight-channel analog input module for the Allen-Bradley FLEX 5000. The values below are limited to the exact documented article.

01

VERIFIED TECHNICAL DATA

Module Designation	FLEX 5000 5094-IF8
Analog Inputs	8 single-ended channels
Channel Isolation	Non-isolated
Current Ranges	0 to 20 mA; 4 to 20 mA
Voltage Ranges	-10 to 10 V; 0 to 5 V; 0 to 10 V
Notch Filter Range	5 to 1000 Hz
Configuration Software	Studio 5000 Logix Designer
Series	Series A
Firmware	2.012
Lifecycle Status	Active

- Refinery separation and storage areas: Drive Coordination Systems
- Solvent recovery and dosing rooms: Quality Inspection Systems
- Sterile filling and packaging cells: Process Control Systems

Match 5094-IF8 to the installed Allen-Bradley FLEX 5000, complete wiring, mating hardware, revision and approved configuration. A similar article number does not establish direct interchangeability.

[Allen-Bradley official manufacturer documentation](#)

Local official manufacturer PDF: 5094-IF8.pdf